

DIE SELECTION GUIDE FOR B15MDE

Copper Tube Connectors

Copper Conductor sqmm Low str. Flex.	Connector		Hexagonal Crimp		Indent Crimp	
	Terminal Lug	Through Connector	Die Set	No. of Crimps*	Die Set	No. of Crimps*
0.25 - 2.5	A03-M A06-M	L03-M L06-M	ME03/2-15	1	MA03/3-15	1
4 - 6	A1-M	L1-M	ME03/2-15	1	MA03/3-15	1
10	A2-M A2-P12	L2-M	ME03/2-15 ME2/3-15	1	MA03/3-15	1
16	A3-M A3-P14	L3-M	ME2/3-15	1	MA03/3-15	1

* No. of Crimps per end for Through Connectors

Nylon Insulated Copper Connectors

Copper Conductor sqmm Flexible	Terminal Lug			Die Set	No. of Crimps
10	ANE2-M	ANE2-P12	ANE2-U	NN4-15	1
16	ANE3-M	ANE3-P14	ANE3-U		1

End Sleeves

Copper Conductor sqmm Flexible	Connector			Die Set
0.3 - 4	PKE 508 - PKE 418	PKC 508 - PKC 418	KE 506 - KE 412	KE4-15
4 - 16	PKE 410 - PKE 1618	PKC 410 - PKC 1618	KE 410 - KE 1616	KE16-15
16	PKE16	PKC16	KE16	KE35-15
25	PKE25	PKC25	KE25	
35		PKC35	KE35	

Further assistance from Cembre Ltd
Tel: 01675 470440 Fax: 01675 470220 E-mail: sales@cembre.co.uk

DIE SELECTION GUIDE FOR B15MDE

Terminal lugs and Through Connectors according to DIN46235 and DIN46267 Pt 1

Copper Conductor sqmm	Connector		Hexagonal Crimp	
	Terminal Lug	Through Connector	Die Set	No. of Crimps*
6	DR6-..	DSV6	MK5/8-15	1
10	DR10-..	DSV10	MK5/8-15	1
16	DR16-..	DSV16	MK5/8-15	1

* No. of Crimps per end for Through Connectors

CS4 Connectors in photovoltaic installations

Copper Conductor sqmm Flexible	Connector	Die Set
2,5 - 4 - 6	CS411 - CS412 - CS420	MCS4-15

Further assistance from Cembre Ltd
Tel: 01675 470440 Fax: 01675 470220 E-mail: sales@cembre.co.uk